

DIODOS ZENER

0,5W	1W	5W
1N746 – 3V3	1N4728 – 3V3	1N5333 – 3V3
1N747 – 3V6	1N4729 – 3V6	1N5334 – 3V6
1N748 – 3V9	1N4730 – 3V9	1N5335 – 3V9
1N749 – 4V3	1N4731 – 4V3	1N5336 – 4V3
1N750 – 4V7	1N4732 – 4V7	1N5337 – 4V7
1N751 – 5V1	1N4733 – 5V1	1N5338 – 5V1
1N752 – 5V6	1N4734 – 5V6	1N5339 – 5V6
1N753 – 6V2	1N4735 – 6V2	1N5340 – 6V0
1N754 – 6V8	1N4736 – 6V8	1N5341 – 6V2
1N755 – 7V5	1N4737 – 7V5	1N5342 – 6V8
1N756 – 8V2	1N4738 – 8V2	1N5343 – 7V5
1N757 – 9V1	1N4739 – 9V1	1N5344 – 8V2
1N758 – 10V	1N4740 – 10V	1N5345 – 8V7
1N962 – 11V	1N4741 – 11V	1N5346 – 9V1
1N759 – 12V	1N4742 – 12V	1N5347 – 10V
1N964 – 13V	1N4743 – 13V	1N5348 – 11v
1N965 – 15V	1N4744 – 15V	1N5349 – 12v
1N966 – 16V	1N4745 – 16V	1N5350 – 13v
1N967 – 18V	1N4746 – 18V	1N5351 – 14V
1N968 – 20V	1N4747 – 20V	1N5352 – 15V
1N969 – 22V	1N4748 – 22V	1N5353 – 16V
1N970 – 24V	1N4749 – 24V	1N5354 – 17V
1N971 – 27V	1N4750 – 27V	1N5355 – 18V
1N972 – 30V	1N4751 – 30V	1N5356 – 19V
1N973 – 33V	1N4752 – 33V	1N5357 – 20V
1N974 – 36V	1N4753 – 36V	1N5358 – 22V
1N975 – 39V	1N4754 – 39V	1N5359 – 24V
1N976 – 43V	1N4755 – 43V	1N5360 – 25V
1N977 – 47V	1N4756 – 47V	1N5361 – 27V
1N978 – 51V	1N4757 – 51V	1N5362 – 28V
1N979 – 56V	1N4758 – 56V	1N5363 – 30V
1N980 – 62V	1N4759 – 62V	1N5364 – 33V
1N981 – 68V	1N4760 – 68V	1N5365 – 36V
1N982 – 75V	1N4761 – 75V	1N5366 – 39V
1N983 – 82V	1N4762 – 82V	1N5367 – 43V
1N984 – 91V	1N4763 – 91V	1N5368 – 47V
1N985 – 100V	1N4764 – 100V	1N5369 – 51V

Código	V(V)	IM(A)
IN 4001	50	1
IN4002	100	1
IN4003	200	1
IN4007	1000	1
IN5061	600	2
BYW95A	200	3
RL25A	400	2,5
RL10	800	1
IN5391	50	1,5
RL201	50	2,0
RL251	50	2,5
IN5900	50	3,0
RL202	100	2,00
RL203	200	2,0